# KEYLIGHT

## **MODEL:**

## **GHIBLI SQ MINI 2 TRIMLESS**





RoHS

IP20

#### ITEM NO: 4932.Δ

### IMPORTANT NOTICE

- To prevent electric shock, turn off electricity at fuse box before installing the lighting fixture, adding or changing
  accessory.
- 2. Ensure a distance of 75mm away from the lighting fixture for air ventilation and make sure to obey all fire regulations.
- 3. The distance between the lighting fixture and to be lighted up object must be at least 500mm.
- 4. Do not touch the lighting fixture when in use.
- 5. Do not cover the lighting fixture by any material at any time.
- 6. When installing or using this lighting fixture, basic safety precautions should always be followed.
- 7. Please refer to a qualified engineer if you have any questions by installation.
- 8. According to the EU Directive WEEE (Waste Electrical and Electronic Equipment) the luminaire must not disposed of via insorted waste. It must be sent to the respective local facility for disposal and/or the recycling of electronic products.

#### INSTALLATION INSTRUCTIONS

- 1. See diagram below, cut installation hole on the ceiling, cut-size 129 X 76mm.
- 2. Put the trimless frame in the ceiling hole, fixed the frame by screw.
- 3. Connect the power supply.
- 4. Take out the outer ring and install the lamp source, then install it.
- 5. Adjust the position then fix the trim and housing, finish installation.

